

SMALL COIL REWINDS Pty. Ltd.
50 EDOLS ST.
NORTH GEELONG.
VIC. 3215
Ph. (03) 5278-8454
Fax. (03) 5272-1659

FITTING REPLACEMENT REGULATORS TO SUZUKI GS-GSX, and OTHERS.

- STEP 1** Remove old voltage regulator / rectifier and fit new unit
- STEP 2** Connect the three **yellow** wires from the voltage rect /regulator to the three **wires from the alternator** windings. (In any order.)
- STEP 3** Connect the **black** wire from the reg./rect. unit to a **good earth**.
- STEP 4** Connect the **red** wire from the reg./rect. unit to the **red** wire in the loom or to the battery positive terminal.
- STEP 5** Connect the **orange OR brown** wire from the reg./rect. unit to an **orange** wire in the loom or to a point which turns power on and off with the ignition switch. (Please use a wire that is on the ignition circuit, this means that it won't loose its reference voltage and still run. As could happen if it is put to a blinker or stop power.) !!!
- STEP 6** Start engine and test voltage at the battery.

Some motorcycle wiring can be confusing. Please consult an auto-electrician or Small Coil Rewinds if in any doubt.

